

Application Note

AN #: 181A

DATE: 30-Oct-98

Page 1 of 1

PYRAMID MODEL #: SVR-200 / SVR-250
RADIO MODEL: Kenwood TK-760/860 mobile
ENGINEER: W. Carlin

APPROVAL INITIALS

ENGINEER _____

DEPT. HEAD _____

Connections:	SVR	Function	Radio	
	Black/Shield	Ground	KCT-19 Pin 6	
	White	Tx Audio Out	KCT-19 Pin 5	
	Blue	Remote enable/disable	External Switch to Ground	
	Green	PTT Out	KCT-19 Pin 8	
	Red	Switched B+	KCT-19 Pin 7	
	Yellow	Rx Audio In	KCT-19 Pin 4	
	Violet	COR	KCT-19 Pin 13	* see note 1
{ Optional }	Brown	Local Mic In	KCT-19 pin 14	* see note 2
	Grey	On Air Detect	N/C	

SVR	JP1	[-]	Remote Enable	SVR	Mobile COR Polarity:	Low
Jumpers:	J1	[In]	Tx audio level	Program:	Mobile Type:	Conv
	J2	[Out]	Tx audio impedance		On-Air Polarity:	Low
	J4	[Out]	Local mic audio loop		Tx Audio Response:	De-emp
	J5	[In]	Local mic PTT loop		Rx Audio Response:	Flat
	J6	[Out]	Local Mic Sensitivity			
	J7	[Out]	Rx Sensitivity			
	J8	[+]	Pull up resistor			

Additional Modifications (SVR-200 / SVR-250): None.

Additional Modifications (Radio): Refer to page 55 of the Kenwood manual for parts location.

1. Solder the two anodes of D205 together to route the audio mute signal out to the KCT-19 cable.
2. If local mic repeat option is enabled, remove the wire from E2 of the KCT-19 (connected to CN2 on the TK-x60 main PCB) and solder it to point "MD" adjacent to IC6.

Revision Number _____

Date _____

Approval Initials _____