

# Application Note

**AN #: 216A**

DATE: 24-Apr-01

Page 1 of 1

**PYRAMID MODEL #:** SVR-200 / SVR-250 / SVR-300

**RADIO MODEL:** Motorola Spectra High Band/High Power /w 9000 Head

**ENGINEER:** W. Carlin

**APPROVAL INITIALS**

ENGINEER

DEPT. HEAD

<b>Connections:</b>	<b>SVR</b>	<b>Function</b>	<b>Logic PCB</b>
	Black/Shield	Ground	P0503 pin 12 (Dig Ground)
	White	Tx Audio Out	P0503 pin 13 (Mic Hi)
	Blue	Remote enable/disable	External Sw to ground
	Green	PTT Out	P0503 pin 17 (PTT)
	Red	Switched B+	P0503 pin 20 (SW B+)
	Yellow	Rx Audio In	P0503 pin 21 (Det. Audio)
	Violet	COR	Audio PA IC (TDA 7256) pin 10
	Brown	Local Mic In	N/C
	Grey	On Air Detect	P0500A pin 15 (K9.4V)

<b>SVR</b>	JP1	[-]	Remote Enable	<b>SVR</b>	Mobile COR Polarity:	High
<b>Jumpers:</b>	J1	[Out]	Tx audio level	<b>Program:</b>	Mobile Type:	Conv
	J2	[Out]	Tx audio impedance		On-Air Polarity:	High
	J4	[In]	Local mic audio loop		Tx Audio Response:	De-Emp
	J5	[Out]	Local mic PTT loop		Rx Audio Response:	Flat
	J6	[In]	Local Mic Sensitivity			
	J7	[Out]	Rx Sensitivity			
	J8	[+]	Pull up resistor			
	J9	[Out]	MCOR Pull up resistor			

**Additional Modifications (SVR-200 / SVR-250 / SVR-300):** None.

**Additional Modifications (Radio):**

Note: All connections (except violet wire, COR) made on under side of HLN6084B Command Board.