

# Application Note

AN #: 191A

DATE: 29-Apr-99

Page 1 of 1

**PYRAMID MODEL #:** SVR-200 / SVR-250

**RADIO MODEL:** Ericsson MLS Mobile

**ENGINEER:** W. Carlin

**APPROVAL INITIALS**

ENGINEER \_\_\_\_\_

DEPT. HEAD \_\_\_\_\_

Connections:	SVR	Function	Radio
	Black/Shield	Ground	J701 Pin 5 {Mic Conn}
	White	Tx Audio Out	J701 Pin 4 {Mic Conn.}
	Blue	Remote enable/disable	External Switch to Ground
	Green	PTT Out	J701 Pin 2 {Mic Conn.}
	Red	Switched B+	IC207 Input {SYS PCB}
	Yellow	Rx Audio In	J707 pin 24 {SYS PCB}
	Violet	COR	J707 pin 12 {SYS PCB}
	Brown	Local Mic In	N/C
	Grey	On Air Detect	N/C

<b>SVR</b>	JP1	[-]	Remote Enable	<b>SVR</b>	Mobile COR Polarity:	Low
<b>Jumpers:</b>	J1	[Out]	Tx audio level	<b>Program:</b>	Mobile Type:	Conv.
	J2	[In]	Tx audio impedance		On-Air Polarity:	Low
	J4	[In]	Local mic audio loop		Tx Audio Response:	De-emp
	J5	[In]	Local mic PTT loop		Rx Audio Response:	Flat
	J6	[In]	Local Mic Sensitivity			
	J7	[Out]	Rx Sensitivity			
	J8	[+]	Pull up resistor			

**Additional Modifications (SVR-200 / SVR-250):** None

**Additional Modifications (Radio):** None

Revision Number \_\_\_\_\_

Date \_\_\_\_\_

Approval Initials \_\_\_\_\_