



AccuMASTER™

Moisture Meter

USER'S MANUAL




**Check your firewood
to see if it's ready to burn**

**Make sure you're getting
dry wood at the lumber yard**

**Measures moisture content
from 6 to 44%**

**Accurate, easy to use,
durable**



Model 7435


USING YOUR AccuMASTER MOISTURE METER

The **AccuMASTER Moisture Meter** is an easy tool to use when measuring moisture in firewood and lumber. Quickly find out if pieces of firewood are ready to burn. When you're at the lumber yard for a building project, make sure you're buying dry, ready-to-use lumber. Woodworkers can save money on expensive pieces of wood for their projects by making sure they are using good, dry wood.


Testing the AccuMASTER

Press the **[On/Hold/Off]** button to turn the unit on.


Remove the protective cap from the top of the meter. Note the two pairs of measurement points on the top.



Touch the **AccuMASTER** pins to the bottom pair of measurement points. Your meter should display →



Now touch the pins to the top pair of measurement points. Your meter should display →



Using the AccuMASTER Moisture Meter

With the unit powered on, carefully press the test pins into the wood you want to measure. The Moisture Content is indicated on the display.

If you want to lock the display, press the **[On/Hold/Off]** button. To clear the current reading press the **[On/Hold/Off]** button again.

To power off the **AccuMASTER** press and hold the **[On/Hold/Off]** button for two seconds.

MOISTURE CONTENT RANGES FOR FIREWOOD

Ideal 6-15%

Good 16-20%

Too wet 21-44%

SPECIFICATIONS

Measuring Range: 6-44%

Accuracy: $\pm 2\%$

Power: 4 AAA 1.5V batteries
(included)

Low Battery Indication: 

Auto Power Off: 3 minutes

Measuring Test Pins:

Stainless steel, replaceable

Part # 7435-PINS

Warranty: 1 year

BATTERY REPLACEMENT

Unscrew the battery compartment lid. Screw is just above the top of the belt clip. Remove batteries and replace with 4 AAA 1.5V batteries. Insert batteries with correct polarity. Replace battery compartment lid and tighten screw.

 **CALCULATED
INDUSTRIES®**

4840 Hytech Drive,
Carson City, NV 89706 USA
www.calculated.com
Made in China • UG7435E-A